



StreetSiren

Wireless outdoor siren

Wireless outdoor siren generates up to 113 dB at a distance of 1 m to deter burglars and attract the attention of neighbors in case of unauthorized trespassing. An inbuilt LED light and beeps indicate the system status. StreetSiren operates on the pre-installed batteries but can be connected to a low current power supply, as well.

Maximum Performance

- Communicates at a distance of up to 1,500 m from the hub
- Operates even at extremely high or low temperatures
- Indicates armed/disarmed states and low battery charge using a built-in LED
- Generates an audible warning if *delay when entering/leaving* mode is activated
- Indicates with sound and light when system's status changes if *beep when arming/disarming* mode is activated
- Operates up to 5 years on the pre-installed batteries and supports external power supply

Effortless Operation

- Adjustable sound level and alarm duration
- Two-way communication with the hub for testing and configuring
- Resists dust, hail and rain drops

Simple Installation



Use the QR code to connect the device to the hub



Use the SmartBracket to mount the device without disassembling it



Open the app to test connection quality and configure device settings

Bulletproof Protection



Tampering and accelerometer alarm



Data encryption



Device forgery prevention

Tech Specs

- Color: white/black
- Radio communication range: up to 1,500 m
- Compatibility: all hubs & ReX
- Type of indication: sound/light
- Adjustable sound volume level: 81–113 dB at a distance of 1 m
- Adjustable alarm duration: 3–180 s
- Battery: 4x CR123A, pre-installed
- Battery life: up to 5 years
- Optional supply: 12 V, 1.5 A DC
- Protection class: IP54
- Operating temperature range: from -25°C to +50°C
- Permissible humidity: up to 95%
- Dimensions: 200x200x51 mm
- Weight: 528 g